



Central Management Software

NET-i viewer

The NET-i viewer is the free monitoring software, which enables the centralized monitoring of Samsung Techwin's DVR and other network products. The NET-i viewer can display up to 64 channels on a monitor or on quad monitors. The event monitoring function provides easy control over alarm events or video loss by use of a yellow boarder on the scene. The search function of NET-i viewer helps in the searching and playback of recorded data on local PC or remote recording device such as DVR/NVR. Calendar search and event search modes are also available, ensuing faster results for users.



Live

Search

Map

- Supports various video format : H.264, MPEG-4, MJPEG
- Supports various audio format : G.726, G.711, G.723
- Supports various video resolution : megapixel (1M, 2M, 3M), 4CIF, Half D1, VGA, CIF
- Powerful E-map based monitoring support
- Bi-directional audio communication
- Remote PTZ control and power area zoom (click and go control)
- Notification in case of event occurring
- Manual recording (up to 1CH) during 24 hours
- Multiple language user interface support
- Easy device management (configuration, firmware upgrade)
- Automatic self upgrade (connection to Samsung upgrade server)

Central Management Software

NET-i viewer



Specifications

NET-i viewer (Version : 1.37)		
DEVICE		
Supported Device	Network Camera, Encoder, DVR, NVR	
Max. Register Device	250	
PERFORMANCE		
Video	Supported Format	H.264, MPEG-4, MJPEG
	Supported Resolution	QXGA, UXGA, SXGA, HD, SVGA, 4CIF, Half D1, VGA, CIF, QVGA
Audio	Supported Format	G.711, G.726, G.723, PCM
	Functions	Bi-directional audio, listen, transmit client microphone input to remote speakers
Live Monitoring	Multi-monitor	Up to 4 monitors (Follow the recommended system requirement)
	Screen-split Mode	1, 4, 6, 7, 8, 9, 10, 11, 12, 16, 25, 36, 49, 64 (Full-screen)
	PTZ Control	PTZ control (Pan, Tilt, Zoom, Focus, Preset) using mouse Digital zoom in/out on the image, click and go control
Search & Playback	Functions	Automatic device search of network cameras for quick and easy configuration, Device management (Configuration & firmware update), Snapshot / Prints image
	Local (Remote) Playback	Supported
	Search	Search for recordings based on DVR, NVR, Date/time based search, Event (Alarm, Motion, intelligent video) based search, POS search
Back up	Playback mode	Normal, Forward/Backward, Fast/Slow, Step
	Functions	Snapshot / Prints image
Event Monitoring	Local (Remote) Back up	Supported
	Back up	Local storage, back up format (AVI, REC1, SEC)
MAP Viewer	Display	Highlighting in the border of video window, Display event log message in real time, Launches instant player
	Logs	Event (Alarm, Motion, Intelligent video, video loss), Stores user actions by time and cameras and full system operation
User Update	Display	Camera / Alarm / Sensor on the map
	Number of Map	50maps
GENERAL	Supports Image Monitoring	JPEG / BMP / GIF / PNG
	Monitoring	Launches instant player/viewer up to 16CH
System Requirement (Recommended)	Admin, Operator, User	
	Update	Automatic self upgrade (Connection to Samsung upgrade server)
Language	Total 24 languages support English, French, German, Spanish, Italian, Russian, Chinese, Japanese, Korean, Turkish, Polish, Czech, Serbian, Romanian, Portuguese, Dutch, Croatian, Hungarian, Greek, Taiwanese, Swedish, Danish, Finnish, Norwegian	
	CPU Intel i7 above, RAM 3GB above, Video memory 1GB above, HDD 200GB above, DirectX 8.1 above. Display resolution : 1,280 x 1,024 above, OpenGL compatible, OS : Window XP Professional, Windows 2000 Professional, Windows Vista Home Basic/Premium/Ultimate, Windows 7 (64bit / 32bit)	

* The entire items are not supported in every device. Some items are not supported in certain devices.

* The latest product information / specification can be found at www.samsungsecurity.com

Supported Models

NET-i viewer (The latest release version : 1.37)

N/W Camera	Box	SNB-7000/5000/3002/3000/2000/1000/1001, SNZ-5200, SNO-7080R/5080R/1080R SNC-B2335/B2331/M300/1300/550/570
	Dome	SND-7080/5080(F)/3082/3080(F)/3080C(F)/1010/1080/1011 SNV-7080/5080/3080/5010/3120/5080R/3082/1080/1080R SND-560/460V, SNC-B5368/B5399
	PTZ	SNP-5200(H)/3430H/3370(TH)/3301(H)/3120(V/VH)/3302(H)/SNP-6200(H) SNC-C6225/C7225/C7478, SNP-3300A/1000A/3750/3350
Encoder	SNS-400/100/101, SPE-400/100, SPE-1600R	
DVR	SRD-1670(D/DC)/1650(D/DC)/870(D/DC)/850(D/DC)/470(D)/440 SRD-1630(D)/1610(D)/830(D), SRD-1652D/852D, SRD-480D/442 SRD-1640/840/1641/841 SVR-1670/3200/1680(C)/1660(C)/1645/960(C)/945/480 SHR-2000/5000/6000/7000/8000 series SVR-1650E/1640A/950E	
	NVR (H/W)	SRN-6450/3250, SNR-6400/3200, SRN-1670D/470D
	NVR (S/W)	NET-i ware : SNS-SF064/032/016/008/004
	N/W Controller	SPC-2000



The Eco mark represents Samsung Techwin's will to create environment-friendly products, and indicates that the product satisfies the EU RoHS Directive.

Design and specifications are subject to change without notice.

SAMSUNG TECHWIN CO., LTD.

701, Sampyeong-dong, Bundang-gu, Seongnam-si, Gyeonggi-do Korea 463-400
Tel : +82-70-7147-8741~8749, 8752~8760 Fax : +82-31-8018-3745
www.samsungipolis.com www.samsungsecurity.com

SAMSUNG TECHWIN AMERICA INC.

100 Challenger Rd. Suite 700 Ridgefield Park, NJ 07660
Toll Free : +1-877-213-1222 Direct : +1-201-325-6920
Fax : +1-201-373-0124
www.samsungcctvusa.com

SAMSUNG TECHWIN EUROPE LTD.

Samsung House, 1000 Hillwood Drive, Hillwood Business Park
Chertsey, Surrey, UNITED KINGDOM KT16 0PS
Tel : +44-1932-45-5300 Fax : +44-1932-45-5325

TIANJIN SAMSUNG TECHWIN OPTO-ELECTRONICS CO., LTD.

No.11 Wei 6 Street, Micro-Electronic Industrial Park
Jingang Road, Tianjin, P.R. CHINA 300385
Tel : +86-22-23887788 Fax : +86-22-23887788

■ DISTRIBUTED BY

